



PRODIGY Series

INTELLIGENT LIGHTING CONTROL




- A compact lighting control system that is simple to connect and configure.
- Scene capture and snapshot editing for rapid state building.
- Scenes can be linked to daily or weekly schedules for automated triggering.
- Smart accompanying outstations provide users with instant access to multiple scenes.
- Supports dimmers and drivers seamlessly across two DMX universes plus Art-Net and DALI.
- Full support for RDM saves time when configuring remote devices.
- In-built network connection allows real-time monitoring and adjustment.
- Power is derived solely by the network connection (PoE or PoE+).



The web-based configuration utility provides quick access from near or far.

Prodigy rear panel



Prodigy specifications

- Input voltage: 48VDC (via PoE or PoE+)
- Main unit power: 5W maximum
- Ingress Protection: IP20 (dry indoor only)
- Front panel functions: Scene Record & DMX Bypass
- Dimensions: 186 x 87 x 186mm
7.32 x 3.43 x 7.32"
- Weight: 2kg (4.4 lbs)
- Temp. range: 0°C to 40°C (32°F to 104°F)

Control outstations



3 fader

Combi

8 button

- Control light levels and recall saved scenes.
- Simple cable link, no extra power required. Can be powered externally for hard-to-reach areas with limited cable infrastructure.
- Easy install via RJ45 connectors.
- AUX Input for additional scene recall.

Accessories



Prodigy 19" rack mount

Prodigy controllers are available with desk, wall or rack mount options for installation in a variety of environments.

Controller and accessories

Prodigy Series Controller
 Wall mount bracket
 Rack mount bracket
 Panel US back box flush mount - black
 Panel US back box surface mount - black
 Panel US back box surface mount - white
 POE injector

Control outstation options

Range	Module	Back Box Type	Colour
Prodigy Series	3 Fader 8 Button Combi	UK US	Black